



Sony NWZ-E473 Screen Replacement

When removing the screen, you may want to use...

Written By: Matthew Hintz



INTRODUCTION

When removing the screen, you may want to use gloves so that no glass shards cut your hands.

TOOLS:


Phillips #00 Screwdriver (1)

iFixit Opening Tool (1)

Tweezers (1)


Spudger (1)

Step 1 — Back Panel



- Use a Phillips #00 screwdriver to unscrew the two 5 mm screws located on the bottom of the back of the device.

Step 2



- Use a plastic opening tool to loosen the bottom portion of device.

Step 3



- Use a plastic opening tool to loosen the top panel of the device.

Step 4



- Use a Phillips #00 screwdriver to remove the two 3 mm screws located on the portion under the top panel of the device.

Step 5



- Remove the back plate from the device.

Step 6 — Screen




- Use a nylon spudger or [tweezers](#) to remove the plastic USB cover.

Step 7




- Use a Phillips #00 screwdriver to unscrew two 2 mm screws located on the top corners of the device.

Step 8



- Use a nylon spudger or tweezers to remove the plastic protective plate at the top of device.

Step 9




- Remove the plastic protective frame located over the motherboard with tweezers and a spudger.

Step 10



- Remove screen connection from motherboard using tweezers and spudger.

Step 11




- Use a Phillips #00 screwdriver to remove two 3 mm screws at the bottom sides and two 1 mm screws at top sides of the device.

Step 12




- Use a Phillips #00 screwdriver to unscrew two 2 mm screws, and remove the motherboard from the device with tweezers and a plastic opening tool.

Step 13



- Disconnect the metal shielding plate from the front panel with tweezers or a plastic opening tool.

Step 14



- Use a plastic opening tool to remove the screen from metal back plate.

To reassemble your device, follow these instructions in reverse order.