




Asus Zenbook UX31E Fan Replacement

This guide will show you how to disassemble the fan on the Asus Zenbook UX31E in the situation that the fan is broken.

Written By: Sinh






TOOLS:

- [T4 Torx Screwdriver](#) (1)
 - [iFixit Opening Tool](#) (1)
-

Step 1 — Back Cover



- Using a T4 Torx screwdriver, remove the ten screws at the marked locations.



i Place the screws into a container as to not lose them.

Step 2




- Carefully slide your iFixit Opening Tool between the back panel.
- Lift the back plate of your ASUS ZenBook UX31E, and place it to the side.

Step 3 — Fan





- Disconnect the ribbon between the IO and the motherboard on both sides.

Step 4





- Disconnect the fan connector from the motherboard.
- Pull up the clips on the ribbon connectors.

Step 5



- Unscrew the two screws that are across each other.

Step 6



- Using a plastic opening tool, lift the fan off of the laptop.
- You can now use your hands and carefully pull the fan off the laptop.

To reassemble your device, follow these instructions in reverse order.