



ZTE Grand X Max Plus Battery Replacement

This guide will show you the steps to remove the battery from your ZTE Grand X Max Plus.

Written By: Jordano Baer



INTRODUCTION

If you have a dead battery and want to replace it, you can use this guide.

The guide will show you how to remove the back cover of the ZTE Grand X Max Plus and how to remove the battery.




TOOLS:


- [Hair Dryer](#) (1)
 - [iFixit Opening Tools](#) (1)
 - [Suction Handle](#) (1)
-

Step 1 — Back Cover



 Make sure you turn off your phone before starting.

- Heat the phone using a heating pad, heat gun, or hair dryer to loosen the glue. You just need to heat the back of the phone.

 You can also use a hair dryer or a heating gun for this step.

Step 2




- After the phone is heated, use the blue plastic opening tool on both sides of the phone.

⚠ Don't apply too much pressure because the cover can crack easily.

ⓘ To avoid that your cover cracks, you can add tape to back cover.

ⓘ You can use a suction cup to help remove the battery.

Step 3



- Carefully remove the cover from the phone.

Step 4 — Battery




- Use a plastic opening tool to pry the battery off.
- ⓘ The battery will be held down securely by glue, so it'll take quite a bit of sliding underneath to separate it from the compartment.

Step 5



- Pull up the piece that is connected to the motherboard. You can pull it using your nails.

Step 6



- Remove the battery.

To reassemble your device, follow these instructions in reverse order.